


INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁵ : H03H 17/06	A1	(11) International Publication Number: WO 94/23493 (43) International Publication Date: 13 October 1994 (13.10.94)
(21) International Application Number: PCT/FI94/00126 (22) International Filing Date: 31 March 1994 (31.03.94) (30) Priority Data: 931532 5 April 1993 (05.04.93) FI (71)(72) Applicants and Inventors: SARAMÄKI, Tapio [FI/FI]; Kreetaninkuja 4 A, FIN-33950 Pirkkala (FI). RITONIEMI, Tapani [FI/FI]; Insinöörinkatu 84 B 31, FIN-33720 Tampere (FI). EEROLA, Ville [FI/FI]; Tohlopinkatu 15 A 2, FIN-33310 Tampere (FI). HUSU, Timo [FI/FI]; Kirkkokatu 12 B 23, FIN-80110 Joensuu (FI). PAJARRE, Eero [FI/FI]; Kanjoninkatu 11 C 26, FIN-33720 Tampere (FI). INGALSUO, Seppo [FI/FI]; Orivedenkatu 8 C 66, FIN-33720 Tampere (FI). (74) Agent: OY KOLSTER AB; Iso Roobertinkatu 23, P.O. Box 148, FIN-00121 Helsinki (FI).		(81) Designated States: CA, JP, KR, US, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published With international search report. In English translation (filed in Finnish).

(54) Title: METHOD AND ARRANGEMENT IN A TRANSPOSED DIGITAL FIR FILTER FOR MULTIPLYING A BINARY INPUT SIGNAL WITH TAP COEFFICIENTS AND A METHOD FOR DESIGNING A TRANSPOSED DIGITAL FILTER

(57) Abstract

The invention relates to a method and an arrangement in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients, and to a method for designing such a filter. The invention comprises a shift register (51, 52) shifting in the direction of the least significant bit and copying the most significant bit or filling in zero values. The register receives the binary input signal of the filter and has outputs for outputting the content of the desired bit positions. A plurality of bit-serial subtractor and adder elements (53-57) multiply the binary input signal by N+1 different tap coefficients by combining output bits of the shift register (51, 52). The subtractor and/or adder elements form a network wherein at least one element participates in the multiplying operation of at least two different tap coefficients.



FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgyzstan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Latvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

Method and arrangement in a transposed digital FIR filter for multiplying a binary input signal with tap coefficients and a method for designing a transposed digital filter

5

The invention relates to a method and an arrangement in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients and to a method for designing such a filter.

10

A digital filter is a software or a specially designed electronic circuit processing discrete signal samples to perform a desired transfer function operation on said signal. The Z transfer function of a digital, i.e. discrete time FIR (Finite Impulse Response) filter has the generic form

15

$$H(z) = \frac{Y(z)}{X(z)} = \sum_{i=0}^N a_i \times z^{-i} \quad (1)$$

20

where $H(z)$ is the transfer function of the filter, $Y(z)$ and $X(z)$ represent the output and input of the filter respectively, a_i represent constant coefficients, i.e. tap coefficients, and z^{-i} represents a delay of i clock cycles. The properties of a FIR filter are solely dependent on the tap coefficients a_i , and thus synthesizing a discrete time filter calls for determining these coefficients so as to provide a filter having the desired characteristics. There are several methods for determining the coefficients. The non-recursive discrete time filter in accordance with equation (1) is normally represented as a block diagram as shown in Figures 1 and 2. Figure 1 illustrates a so-called direct-type FIR (Finite Impulse Response) filter and

25

30

Figure 2 a transposed FIR filter. The filtering function in accordance with equation (1) can be realized by both discrete time filters, but the present invention relates to a transposed FIR filter according to Figure 2. As is apparent from Figures 1 and 2, the discrete time filter is illustrated as a block diagram wherein square blocks 1 perform delaying of the information by one clock cycle z^{-1} , triangular blocks 2 represent multiplying operations and circles 3 represent adders.

As stated previously, the characteristics of the filter are dependent on the values of the tap coefficients a_i . In certain prior art transposed FIR filters, a discrete multiplier unit for each tap coefficient is employed. The drawback of this arrangement is the large number of multiplier units required, which occupy a considerable area on a chip when realized as an integrated circuit and are therefore costly. One known implementation is such wherein the tap coefficients are simple sums of powers of two, i.e. the coefficients are limited to the form $2^{-a}+2^{-b}+2^{-c}$. Such a solution is attended by the drawback of limitations in the possible coefficients to be realized. These limitations can substantially complicate the realization of the desired signal processing function $H(z)$.

Still another known solution entails the use of a fast multiplier and memory for realizing the filter. Such a solution is illustrated in Figure 3, wherein the necessary delays z^{-1} are generated by buffering the values of the input signal $X(z)$ into a RAM memory 41 prior to their application to a multiplier 42, where they are multiplied by existing coefficients a_i obtained from a ROM memory. Thereafter the multiplication results are applied to an adder 44 wherein they are summed together with the filter output $Y(z)$. The drawback of such a solution is the chip area occupied

by the fast multiplier unit 42. Further drawbacks include the power consumption of the multiplier unit 42 and, in certain applications, the electromagnetic interference produced thereby in other circuit structures. Furthermore, on account of the limited speed of the multiplier unit, only a limited number of coefficients a_i can be realized with one multiplier unit. Complex structures require several multiplier units and complex control logic.

The object of the present invention is a transposed digital FIR filter that can be realized as an integrated circuit with several coefficients so as to occupy a substantially smaller chip area in integrated circuit configuration than that occupied in the prior art techniques.

Another object of the present invention is a filter structure suitable for comparatively high clock frequencies, since the speed of the filter structure is not dependent on the requisite number of coefficients.

A further object of the present invention is a digital filter enabling realization of arbitrary coefficients automatically.

These and other objects and advantages of the invention are achieved with a method in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients, which method is characterized in accordance with the invention in that multiplications are performed by using a network of subtractor and/or adder elements wherein at least one element participates in multiplying by at least two different tap coefficients.

Another aspect of the invention is an arrangement in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients. The arrangement is characterized in accordance with the invention

in that it comprises a shift register shifting in the direction of the least significant bit and copying the most significant bit or filling in zero values. The register receives the binary input signal of the filter and has outputs for outputting the content of the desired bit positions, a plurality of bit-serial subtractor and adder elements for multiplying the binary input signal by $N+1$ different tap coefficients by combining output bits of the shift register. The subtractor and/or adder elements are configured as a network wherein at least one subtractor and/or adder element participates in the multiplying operation of at least two different tap coefficients.

One aspect of the invention is a method for designing a transposed digital filter. This method is characterized in accordance with the invention by determining the tap coefficients required in the filter and designing for the filter a network of subtractor and/or adder elements performing the multiplication by tap coefficients, wherein the number of elements is minimized taking into account certain performance criteria for the filter, so that a maximum number of elements participate in the multiplying operation of more than one different tap coefficients.

In the present invention, the tap coefficients are realized by combining numbers divided by powers of two with bit-serial adder and/or subtractor elements, so that at least some of the adder and/or subtractor elements are used for realizing more than one coefficient. In accordance with the invention, all necessary values multiplied by numbers of the form 2^{-n} are obtained simultaneously from one shift register. In other words, the "partial sum" or "partial difference" produced by a specific element can be used on the next level of the network of adder and/or subtractor ele-

ments simultaneously to form several coefficients. Further, in the arrangement according to the invention the combined use of adder and subtractor elements in producing the coefficients enables the number of elements (+/- operators) to be minimized. It is further possible to minimize the rounding error related to the coefficients by "balancing" the operators against each other.

By means of the invention, the network of bit-serial adder and subtractor elements can be optimized by finding the sum and/or difference of powers of two for the coefficients required, so as to considerably diminish the requisite number of calculation elements in comparison with the prior art solutions. For instance, if a coefficient accuracy of 20 bits is required, ten adder stages on an average are needed for each coefficient in the prior art implementation. With a design according to the invention, it is possible to realize the coefficients with three adder and/or subtractor stages for each coefficient. At the same time, the number of series-connected elements required is characteristically diminished. With the construction of the invention, arbitrary coefficients can be realized. A still another advantage of the invention is a low number of logic levels, and thus the maximum operating frequency is very high. When the invention is realized as an integrated circuit, the silicon area occupation required is less than half the area required by the filter shown in Figure 3 which includes a multiplier and RAM and ROM memories.

In the following the invention will be set forth by means of illustrating embodiments with reference to the accompanying drawing, wherein

Figure 1 is a block diagram of a direct-type digital FIR filter,

Figure 2 is a block diagram of a transposed digital FIR filter,

Figure 3 is a block diagram of a prior art digital filter implemented with a fast multiplier and memories,

Figure 4 is a block diagram of a digital filter of the invention with four coefficients, and

Figure 5 is a block diagram of a bit-serial adder element.

Reference will now be made to Figure 4, showing a four-coefficient transposed digital FIR filter realized in accordance with the invention. The filter comprises a series connection of three filtering stages, each filtering stage comprising a delay block 58, 59 and 60 having a length of one word (z^{-1}) and an adder element 61, 62 and 63 connected thereafter, the output signal of each delay block being applied to the corresponding adder element and the output signal of each adder element being applied to the next delay block. The output of the last adder element 63 constitutes the output Y of the entire filter.

The binary input signal X of the filter is first applied in serial form to a serial/parallel converter 51 wherefrom it is copied into a series-type shift register 52. The number copied into the shift register 52 can be shifted bit by bit in the direction of the least significant bit LSB. Upon this, the shift register 52 adds X most significant bit MSB of the number copied into the shift register to the most significant end MSB of the shift register if the number X is in the 2's complement form. Otherwise, zeros are filled in as the most significant bits.

The shift register 52 has outputs for outputting the content of all bit positions or the desired bit positions.

A network of combining elements is coupled between the selected outputs of the shift register 52 and series-connected filtering stages 58-63 for multiplying the input signal X by tap coefficients a_1 , a_2 , a_3 and a_4 of the filter by combining output bits of the shift register 52, i.e. powers of two. The network comprises bit-serial adder and subtractor elements employing bit-serial arithmetic and being arranged in several levels. In accordance with the basic concept of the invention, it has been sought to minimize the number of calculation elements taking into account certain performance criteria for the filter, so that the same calculation elements are employed to produce more than one different tap coefficients. In the exemplary case of Figure 5, four coefficients are formed employing only five bit-serial arithmetic elements 53, 54, 55, 56 and 57. For instance, the inputs of the subtractor element 53 are provided by bit position outputs 2^{-0} and 2^{-3} of the shift register. On the one hand, the output value $X - (X/8)$ of the subtractor element 53 directly provides one of the output values a_4x of the entire network, and this value is applied to the adder element 63 to be summed together with the output of the delay block 60, and on the other hand it forms an intermediate result that is applied as another input to the adder element 54. The other input of the adder element 54 is provided by bit position output 2^{-5} of the shift register 52, and the output of the element 54 constitutes one output value a_3x for the entire network, said value being applied to the adder element 62 to be summed together with the output of the delay block 59. The inputs of the adder element 55 are provided by bit position outputs 2^{-3} and 2^{-5} of the shift register 52. The adder element 55 forms a subtotal that is applied to both the adder element 56 and the subtractor element 57. The

other input of the adder element 56 is provided by bit position 2^{-10} of the shift register 52, and the output of the element 56 constitutes one output a_1x for the entire network, said value being applied to the first delay block 58 connected in series. The other input of the subtractor element 57 is provided by bit position output 2^{-8} of the shift register 52, and the output of the element 57 constitutes one output a_2x for the entire network, said value being applied to the adder element 61 to be summed together with the output of the delay block 58. Thus in the filter of Figure 4 the element 53 participates in the calculation of both coefficient a_3 and coefficient a_4 . Likewise, the adder element 55 participates in producing both coefficient a_1 and coefficient a_2 .

The filter according to Figure 4 operates in the following way. The first binary number of the discrete time signal of the filter is initially applied to the serial/parallel converter 51 wherefrom it is copied into the series-type shift register 52 in such a way that the least significant bit of the number X is positioned at bit position 2^{-0} of the register 52. The serial/parallel converter 51 and the shift register 52 thus constitute a kind of dual shift register wherein the serial/parallel converter 51 serves as a buffer into which the signal from the preceding signal processing stage can be received whilst the number in the shift register 52 is being processed by the filter of the invention. When the number X has been loaded into the shift register 52, the first calculation is performed, as a result of which the least significant bit of number Y is obtained at the filter output. Thereafter the number X is shifted in the shift register 52 one bit position to the right, i.e. in the direction of the least significant bit LSB, and a new

calculation is performed to provide the next more significant bit of the number Y at the filter output. The rightward shifts in the shift register 52 and the resultant calculations are continued, providing further bits in the number Y at the filter output, until the desired accuracy has been achieved. Thereafter the next number is loaded from the serial/parallel converter 51 into the shift register 52.

Figure 5 shows a block diagram of a bit-serial adder element. The adder element comprises a one-bit delay element 61, which in this exemplary case is realized by means of a D flip-flop, and an adder 62 adding two data bits together and outputting a sum and a carry bit c_{out} . All signals shown in Figure 5 are one-bit signals, i.e. each of them can be realized by means of a single signal line.

The adder element shown in Figure 5 operates in the following way. The numbers to be summed together are applied to the adder 62 in serial form, the least significant bit (LSB) being the first. The addition of two bits a and b and a carry bit c_{in} gives as a result one sum bit sum and a carry bit c_{out} which is stored in the delay element 61 for summing together the next bits. The delay element 61 is reset between the addition of two successive n-bit numbers, by means of the reset line.

The bit-serial subtractor element can be realized similarly. The only difference is that instead of an adder 62, a subtractor is employed. Furthermore, the delay element 61 is set to the value 1 between the subtraction of two successive n-bit numbers.

The figures and the description relating to them are only intended to illustrate the present invention. In their details, the methods and filter of the invention can vary within the purview of the accompanying

claims.

Claims:

1. A method in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients, c h a r a c t e r i z e d in that
5 multiplications are performed by using a network comprising subtractor and/or adder elements wherein at least one element participates in multiplying by at least two different tap coefficients.
- 10 2. An arrangement in a transposed digital FIR filter for multiplying a binary input signal by tap coefficients (a_1, a_2, a_3, a_4), c h a r a c t e r - i z e d in that the arrangement comprises
15 a shift register (51, 52) shifting in the direction of the least significant bit and copying the most significant bit or filling in zero values, for receiving the binary input signal of the filter and having outputs for outputting the content of the desired bit positions,
20 a plurality of bit-serial subtractor and adder elements (53-57) for multiplying the binary input signal by $N+1$ different tap coefficients by combining output bits of the shift register (51, 52), said subtractor and/or adder elements forming a network wherein
25 at least one element participates in the multiplying operation of at least two different tap coefficients.
3. An arrangement as claimed in claim 2, c h a r a c t e r i z e d in that the shift register is a dual shift register (51, 52).
- 30 4. An arrangement as claimed in claim 3, c h a r a c t e r i z e d in that the first part of the shift register is a parallel/serial converter (51), the number applied to said converter being loaded in parallel form into the second part (52) of the shift
35 register.

5. A method for designing a transposed digital filter, characterized by determining the tap coefficients required in the filter,

- 5 designing for the filter a network of bit-serial subtractor and/or adder elements performing the multiplication by tap coefficients, wherein the number of elements is minimized taking into account certain performance criteria for the filter, so that a maximum
- 10 number of elements participate in the multiplying operation of more than one different tap coefficients.




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5

INTERNATIONAL SEARCH REPORT

International application No.

PCT/FI 94/00126

A. CLASSIFICATION OF SUBJECT MATTER

IPC5: H03H 17/06

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC5: H03H

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

SE,DK,FI,NO classes as above

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US, A, 5025406 (O. KLANK ET AL), 18 June 1991 (18.06.91), figure 3, claim 1 --	1
X	EP, A2, 0492578 (ADVANTEST CORPORATION), 1 July 1992 (01.07.92), figure 4, claim 4 --	2
A	US, A, 5031133 (E. SASAKI), 9 July 1991 (09.07.91), the whole document -----	1-5

☐ Further documents are listed in the continuation of Box C.☒ See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

20 July 1994

Date of mailing of the international search report

26.07.94

Name and mailing address of the ISA

Swedish Patent Office

Box 5055, S-102 42 STOCKHOLM

Facsimile No. +46 8 666 02 86

Authorized officer

Rune Bengtsson

Telephone No. +46 8 782 25 00

INTERNATIONAL SEARCH REPORT
Information on patent family members

02/07/94

International application No.

PCT/FI 94/00126

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US-A- 5025406	18/06/91	DE-A- 3841268 EP-A- 0372440	13/06/90 13/06/90
EP-A2- 0492578	01/07/92	AU-B- 632722 AU-A- 9008191 CA-A- 2058310 JP-A- 4270510 US-A- 5313412	07/01/93 09/07/92 29/06/92 25/09/92 17/05/94
US-A- 5031133	09/07/91	AU-B- 624682 AU-A- 4989690 EP-A- 0383326	18/06/92 23/08/90 22/08/90